

Error codes of Guardant SLK[..]

05/20/2025 05:37:26

[FAQ Article Print](#)

Category:	FAQ in English::Software Protection	Last update:	04/09/2025 12:34:43
State:	public (all)		

Keywords

Guardant

Problem (public)

Error codes of Guardant SLK technology

Solution (public)

0: The operation was completed successfully.
1: Invalid session descriptor
2: The requested component (Feature) was not found
3: The resource of network licenses for the component (Feature) is exhausted
4: Unacceptable license conditions for the component (Feature)
5: Incorrect serial number
6: Invalid license file
7: The license has not been activated
8: The license has already been activated
9: Error in obtaining hardware components for license binding
10: There are not enough hardware components to bind the license.
11: License activation is prohibited on a VM
12: Error sending a request to the activation server
13: Error receiving response from activation server
14: Activation server not found
15: An incorrect response was received from the activation server
16: Error in creating the license file
17: The number of activations for the serial number has been exhausted
18: No license updates found
19: The license cannot be activated, please contact the vendor
20: No information about the buyer is provided
21: The redistributable license cannot be activated
22: The license cannot be activated with the driver (API) installed
23: Invalid parameter
24: Insufficient buffer size, operation cannot be performed
25: An internal API error has occurred
26: The license is blocked by the vendor
27: No licenses available
28: The counter for the component (Feature) has been exhausted
29: The license period for the component (Feature) has expired
30: Invalid public key for signature verification
31: Operation is not supported
32: No access to the runtime environment
33: The Guardant key was not found
34: No results found
35: Invalid data buffer or digital signature value
36: The period of use of the component (Feature) has not yet arrived or the component (Feature) is not active.
37: Accessing memory outside its range
38: Access is denied
39: The number of password attempts has been exhausted
40: The specified serial number was not found on the server
41: An invalid memory identifier is specified or the item does not exist.
42: Startup detected in a virtual environment
43: Remote desktop startup detected
44: Outdated version of the Guardant Control Center is prohibited on the VM
45: Rehost is not allowed
46: DL storage corrupted
47: DL storage ID mismatch (input is not intended for current storage)
48: Invalid update for DL received or update has been installed before
49: Invalid rehost dat? sent to server
50: Hardware ID mismatch
51: Reactivation is not allowed because of license contains write memory or features with counter
52: Recipient has the same license activated as the license trying to rehost to it
53: Detach failed for some of chosen features
54: Required cancel previous detach before making new one
55: Detached license already expired
56: Detached license not found
57: Detach forbidden by Gurdant Control Center
58: Trial license expired
59: Operation is not allowed
60: Timer error